

Project : Multi_IO

Version : 1.36

Comments : Universal IO functionality for the multi-16 PLC

Physical connections

=====

Measurements

- 60,61 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 62,63 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 64,65 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 66,67 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 68,69 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 70,71 Digital Indication / Temperature measurement (NTC10) / Resistance (Ohm) / 10k Potentiometer
- 72,73 Voltage measurement (0-100%)
- 74,75 Voltage measurement (0-100%)

0..10V outputs

- 80,81 AO1 output (0-100%)
- 82,83 AO2 output (0-100%)
- 84,85 AO3 output (0-100%)
- 86,87 AO4 output (0-100%)

Modbus Registers

=====

Reg8	Potentiometer AI1 (-100% - 100%)
Reg9	Potentiometer AI2 (-100% - 100%)
Reg10	Potentiometer AI3 (-100% - 100%)
Reg11	Potentiometer AI4 (-100% - 100%)
Reg12	Potentiometer AI5 (-100% - 100%)
Reg13	Potentiometer AI6 (-100% - 100%)
Reg14	Resistance AI1 (Ohm)
Reg15	Resistance AI2 (Ohm)
Reg16	Resistance AI3 (Ohm)
Reg17	Resistance AI4 (Ohm)
Reg18	Resistance AI5 (Ohm)
Reg19	Resistance AI6 (Ohm)
Reg20	Temperature AI1 (°C - NTC10)
Reg21	Temperature AI2 (°C - NTC10)
Reg22	Temperature AI3 (°C - NTC10)
Reg23	Temperature AI4 (°C - NTC10)
Reg24	Temperature AI5 (°C - NTC10)

Reg25	Temperature AI6 (°C - NTC10)	
Reg26	Voltage measurement AI7 (0-100%)	
Reg27	Voltage measurement AI8 (0-100%)	
Reg28	AO-output 1 (0-100% - 0..10V)	
Reg29	AO-output 2 (0-100% - 0..10V)	
Reg30	AO-output 3 (0-100% - 0..10V)	
Reg31	AO-output 4 (0-100% - 0..10V)	
Reg32	Digital Input 1	Reg38 muss grösser oder gleich sein >= 2
Reg33	Digital Input 2	Reg38 muss grösser oder gleich sein >= 2
Reg34	Digital Input 3	Reg38 muss grösser oder gleich sein >= 2
Reg35	Digital Input 4	Reg38 muss grösser oder gleich sein >= 2
Reg36	Digital Input 5	Reg38 muss grösser oder gleich sein >= 2
Reg37	Digital Input 6	Reg38 muss grösser oder gleich sein >= 2
Reg38	DigitalInput off-delay in seconds (used for all digital inputs)	
Reg51	DI 1 open/closed selection (0=normally open, 1=normally closed)	
Reg52	DI 2 open/closed selection (0=normally open, 1=normally closed)	
Reg53	DI 3 open/closed selection (0=normally open, 1=normally closed)	
Reg54	DI 4 open/closed selection (0=normally open, 1=normally closed)	
Reg55	DI 5 open/closed selection (0=normally open, 1=normally closed)	
Reg56	DI 6 open/closed selection (0=normally open, 1=normally closed)	

Reg64+Reg65 Resistance AI1 (Ohm - 32 bit - 64=MSB, 65=LSB)

Reg66+Reg67 Resistance AI2 (Ohm - 32 bit - 66=MSB, 67=LSB)

Reg68+Reg69 Resistance AI3 (Ohm - 32 bit - 68=MSB, 69=LSB)

Reg70+Reg71 Resistance AI4 (Ohm - 32 bit - 70=MSB, 71=LSB)

Reg72+Reg73 Resistance AI5 (Ohm - 32 bit - 72=MSB, 73=LSB)

Reg74+Reg75 Resistance AI6 (Ohm - 32 bit - 74=MSB, 75=LSB)